

# USB To RS-422 / 485 Converter

## US-101-485



- USB
  - ✧ Chipset : Silicon Laboratories CP2102
  - ✧ Compliant : USB 1.0 , 1.1 , 2.0
  - ✧ Connector : USB type A
  - ✧ Baud Rates : Full speed 12 Mbps
- Serial Port
  - ✧ Port : 1 port ( Terminal Block )
  - ✧ RS-422 : RxD+ , RxD- , TxD+ , TxD- ,
  - ✧ RS-485 : Data+ , Data-
  - ✧ RS-422 , RS-485 Auto Detect
  - ✧ RS-422 , RS-485 Surge Protect
  - ✧ Receive buffer : 576 Byte
  - ✧ Transmit buffer : 640 Byte
  - ✧ Baud Rate : 300 ~ 230.4 K bps
  - ✧ Flow Control : X-On / X-Off or Hardware
- Driver Support
  - ✧ Windows -98SE / 2000 / XP / Server 2003 / Mac osx / os9 / Linux 2.4 / 2.6
- Power : USB Bus Power ( 5V )
- Dimension
  - ✧ Size : 55 \* 40 \* 25 mm ( W \* D \* H )
  - ✧ Weight : 35 gm
- Environment
  - ✧ Operating Temp : 0~60°C
  - ✧ Storage Temp : -20 to 85°C
  - ✧ Humidity : 5~95 % RH

